intel®

APPLICATION NOTE

AP-29

August 1977

Using the Intel 8085 Serial I/O Lines

John Wharton
Microcomputer Applications

9800684A

Using the Intel 8085 Serial I/O Lines

Contents

INTRODUCTION 1
- MCS Family Members 1
- Additional 8085 Instructions 1

CRT INTERFACE 3
- Hardware Interface 3
- Software Package 3
  - OUTPUT ROUTINE 5
  - INPUT ROUTINE 6
  - TIMING ANALYSIS 6
  - BAUD RATE IDENTIFICATION ROUTINE 7

CASSETTE RECORDER INTERFACE 8
- Hardware Design 8
- Software 9
  - OUTPUT ROUTINE 10
  - INPUT ROUTINE 10

ADDITIONAL COMMENTS 12

APPENDIX 13

INTRODUCTION

This application note is intended to acquaint the reader with the Intel® MCS-85 family, and to explain how to use one of its key features, a direct serial data link between the CPU and the outside world. Two design examples will be provided: a versatile method for direct communications between the CPU and a CRT or other peripheral at any rate from 110 to 9600 baud, and a magnetic tape interface system which allows programs and data to be stored or loaded using a cheap audio cassette recorder. Both examples use software routines to replace extensive external hardware and to provide additional flexibility.

MCS Family Members

The MCS-85 family consists of the new 8085 N-channel, 8-bit microprocessor (Figure 1) and a variety of parts which provide memory, input/output, timing, and peripheral control capability.



Figure 1. 8085 Pinout Diagram

In many respects the 8085 can be thought of as simply a hardware refinement of the extremely popular Intel® 8080 processor, which was introduced in 1973. It is 100% software-compatible with its predecessor. In addition to being 50% faster, many of the external timing and control functions needed by the 8080A have been integrated into the 8085 (such as the 8224 Clock Generator and the 8228 System Controller), thus reducing the system part count. Additional features include four additional maskable and non-maskable interrupt pins, increased drive capability, and two new input and output lines. These pins, called SID and SOD, provide a serial I/O data link with the CPU. The 8085 uses a standard 40-pin DIP package.

All members of the MCS-85 family require a single 5-volt power supply, greatly reducing system overhead. Several components combine a number of system functions (e.g., ROM and I/O), allowing a complete, useful microcomputer system to be assembled with as few as three integrated circuits, as shown in Figure 2. For example, the 8155 and 8156 RAM/IO/TIMER chips each contain 256 8-bit bytes of program or data storage, three programmable I/O ports, and a 14-bit timer/counter.

Since the internal architecture and instruction set of the 8085 is an extension of that of the 8080, all software written for the 8080 – including compilers, assemblers, and individual applications programs – will run without modification on the new processor. In fact, the complete upward compatibility of the MCS-85 system means that applications designed around the 8080 can be converted to using the 8085 at minimal cost, requiring little hardware redesign or program modification. An engineer already familiar with the 8080 will not need to learn a new architecture or mnemonics. Companies now using Intel's extensive line of design, development, and debugging tools can augment their systems with a series of 8085 support products (such as the SDK-85, ICE-85, and SBC boards) which are compatible with their present mainframe and peripherals.

Additional 8085 Instructions

The additional hardware features of the 8085 (handling multiple-level maskable interrupts and serial I/O) are supported with two new instructions. RIM (machine code 20H) is used to read the current status of the three interrupt masks into the accumulator. Additional bits are set to show what interrupts (if any) are pending, and the logical state of the SID input pin (pin 5). The complement of RIM is SIM (machine code 30H), which has a dual function depending on the current accumulator contents. If bits 3 or 4 of the accumulator are a logical one, SIM can be used to change the three

interrupt masks; if bit 6=1, SIM can set the SOD output (pin 4). The two functions of the SIM instruction operate independently. (If, at this point, the acronyms RIM, SIM, SID, and SOD are starting to blur in your mind, try to remember their roots instead: Read Interrupt Mask, Set Interrupt Mask, Serial Input Data, and Serial Output Data. Don't worry; of the other four ordered permutations of R&S, I&O, and M&D, only ROM is used elsewhere in this note, and then only in its traditional sense.)



Figure 2. 8085 Minimum System

A detailed explanation of the accumulator contents after and before RIM and SIM is given in Figure 3. The I/O pins both function with respect to positive logic: a "1" in the accumulator corresponds to a high voltage level, "0" to a level near ground. The SID and SOD lines are electrically compatible with normal TTL logic levels. (For full electrical specifications, the reader should consult the MCS-85 User's Manual.) If A_6 is "0" prior to executing SIM, SOD will remain unchanged, regardless of the state of A_7. After a Reset, SOD will be low. It should be noted that RIM does not affect the Sign Flag; in order to make a conditional jump based on the Serial Input Data state, a three instruction sequence should be used, such as shown in Examples 1 and 2. When serial data is to be assembled into a parallel word, a sequence such as in Example 3 can be used, which shifts the contents of register pair HL one bit to the left and appends the input data bit.



Figure 3. Effect of RIM and SIM Instructions

This note does not concern itself with the interrupt mask manipulation also made possible with RIM and SIM; for a full understanding of the interrupt capabilities of the 8085, see the User's Manual. To use SIM for altering the SOD state without fear of interfering with the interrupt mask status, one need only make sure that bits 3 and 4 of the accumulator are set to zero first.

```
EXAMPLE 1:
XXX
RIM             ;READ SID LEVEL
ORA     A       ;SET SIGN FLAG IF A7=1
JN      LABEL   ;JUMP IF SID WAS HIGH.
XXX             ;\ ELSE CONTINUE.

EXAMPLE 2:
XXX
RIM             ;READ SID
RAL             ;MOVE A7 INTO CY
CNC     SERVICE ;CALL SERVICE ROUTINE
                ;\ IF SID WAS LOW.
XXX             ;\ THEN CONTINUE.

EXAMPLE 3:
XXX
RIM             ;READ SID DATA BIT
RAL             ;MOVE DATA INTO CY
MOV     A,L
RAL             ;ROTATE DATA INTO L
MOV     L,A
MOV     A,H
RAL             ;ROTATE OVERFLOW
MOV     H,A     ;\ INTO H
XXX             ;CONTINUE
```

On the following pages, examples are given showing two possible uses of the SID and SOD lines. The main purpose of these examples is not to give the reader a design after which he could model his own system – though, of course, this might be the case – but rather to illustrate the hardware and software interfaces and techniques necessary to implement a typical working subsystem.

CRT INTERFACE

Most microprocessor systems require some sort of serial communications. This may be selected for reasons of economy (to reduce the number of interconnections required in a distributed system), or it may be necessary in order to communicate with such common peripherals as CRT's or teletypewriters.

These peripherals all use a standard convention for transmitting serial ASCII code. Each data byte is transmitted as a series of 10 or 11 bits. The uniform time per bit corresponds to the data transmission rate. For example, if the transmission rate is to be 2400 baud (2400 bits per second), each bit time must be 1/2400 bps = 416.7 μsec/bit. The standard 10-bit sequence consists of a logically zero "Start" bit, 8 data bits (least significant bit first), and one or more stop bits (logic 1). An 11-bit sequence with two stop bits is used for 110 baud TTY's. The logic one level continues until the start bit of the next byte to ensure that each 10-bit sequence is initiated with a one-to-zero transition. The 8 bits transferred might be raw binary data or alphanumeric characters using the standard ASCII code. In this case, the most significant bit – the last data bit transmitted – will depend on the parity convention being used. This sequence is illustrated for the ASCII "space" character in Figure 4.



Figure 4. ASCII Space Character

The algorithm for receiving serial code involves sampling the incoming data at the middle of each bit time. The eight sampled values are shifted into a serial byte corresponding to the data originally transmitted. The one-to-zero transition at the beginning of each byte makes it possible to synchronize the sampling points relative to the start of each data sequence.

Hardware Interface

In general, any serial communications system will require both hardware and software interfaces. Since the SOD line can drive only one TTL load, additional current and voltage buffering is required to be compatible with the RS-232C interface standard used by most peripherals. A schematic for achieving this buffering is shown in Figure 5. The MC1488 and MC1489 circuits interface positive logic TTL signals with the RS-232 high voltage inverted logic levels.

Software Package

The software needed to drive the CRT interface is divided into three parts. All three use software timing and delay loops, with fixed and variable parameters. In conjunction, they are able to identify incoming signals at any rate from below 110 to over 9600 baud and respond at the same rate.



Figure 5. RS-232C Interface Schematic

Upon power-up or reset, or when the console device baud rate is changed, the baud rate identification subroutine (BRID) is called. This routine waits until an ASCII space character (20H) is received from the console. (Any other character will result in a case of mistaken identification.) When a space character is received, two time parameters are computed which correspond to the bit time and one-half the bit time of the baud rate being used. These are stored as variables BITTIME and HALFBIT. To output a character to the console, the character code is placed in register C, and the subroutine COUT is called. This routine uses BITTIME as a parameter for the software delay loop which determines the baud rate. To accept a character from the keyboard, CIN is called. CIN returns after the next key is typed, with the corresponding character code in register C. CIN uses both parameters BITTIME and HALFBIT.

Since COUT and CIN use time parameters computed by BRID, they will function at a rate the same as that of the initial space character input. Because of the nature of the software, the rate does not depend on the CPU clock frequency. This results in additional flexibility in the following respects:

1. The software does not need to be modified if the 8085 crystal frequency is changed or Wait states are added.
2. Since the time base is no longer critical, the quartz crystal could be replaced by a less expensive RC network, provided the frequency does not drift by more than a few percent during a session. Additional drift can be accommodated by periodically recalling the BRID routine.
3. Communication is possible at non-standard baud rates which relaxes the constraints on system peripherals.

It should be noted, though, that slowing down the CPU clock will decrease its throughput proportionately. In addition, it will degrade the maximum resolution of the delay loops, with the result that the highest baud rates may no longer be achievable.

A more detailed analysis of the CRT interface routines will be presented in the order of increasing complexity: COUT, CIN, and BRID. Since SID and

SOD are ideal for many applications which involve critical I/O timing, the timing techniques used here may be of interest to software designers. Accordingly, the mathematical derivation of the timing parameters is included in this analysis, as well as a justification for the BRID algorithm. The algebra involved might be a bit too tedious for designers unconcerned with generating software delays. If so, they (and other bored readers) have the freedom of choice to skip over the sections they find objectionable.

OUTPUT ROUTINE

It would seem natural to write data in the standard format in three stages: output a zero start bit, then the 8 data bits (using a loop sequence), then the stop bits. Each stage would incorporate its own appropriate delay and output sections, leading to unnecessary duplication. Instead, the code below executes the same main loop 11 times. Its bit manipulation routine inherently results in the correct data sequence being formed. It accomplishes this by using the carry and C register as a 9-bit pseudo-circular shift register. Initially CY=0. The algorithm outputs CY, waits one bit time, sets CY=1, and then rotates the pseudo-register right one bit. This repeats for 11 cycles. On the tenth and all subsequent loops, the output bit will be a logical one, since that bit had been set nine loops earlier while in the CY (see Figure 6).

When COUT is called the registers to be used must be preserved and interrupts disabled so the timing loop will not be disrupted. Clear the CY in preparation for outputting the start bit, and set the loop counter for 11 bits (if 110 baud will never be used, the counter could be set to 10):

```
COUT:   PUSH    B
        PUSH    H
        DI
        XRA     A
        MVI     B,11
```

Output of the contents of the CY:

```
C01:    MVI     A,80H       <7>
        RAR                 <4>
        SIM                 <4>
```

The numbers in brackets indicate how many machine cycles are required for each instruction. They will be referred to in the timing analysis section.



Figure 6. Data Serialization Algorithm

Get stuck in a loop for the appropriate time (don't worry for now how "BITTIME" is determined):

```
        LHLD    BITTIME     <16>
C02:    DCR     L           (D)
        JNZ     C02         (D)
        DCR     H           (D)
        JNZ     C02         (D)
```

Rotate the contents of register C right into the CY, while moving a one into the left end. Continue until all bits have been transmitted:

```
        STC                 <4>
        MOV     A,C         <4>
        RAR                 <4>
        MOV     C,A         <4>
        DCR     B           <4>
        JNZ     C01         <10>
```

Restore processor status and return:

```
        POP     H
        POP     B
        EI
        RET
```

INPUT ROUTINE

The console input routine uses the opposite procedure; instead of moving a bit from register C to the CY, then to A_7, then to SOD, CIN loads a bit from SID into A_7, then moves it to CY, then into register C.

First, set up the CPU as before:

```
CIN:    PUSH    H
        DI
        MVI     B,9
```

When a start bit transition arrives, the first sampling should not be taken until the middle of the first data bit, one and one-half bit times after the transition. Await the start bit transition, then set up the delay parameter for one-half bit time:

```
CI1:    RIM             ⟨4⟩
        ORA     A       ⟨4⟩
        JM      CI1     ⟨7⟩
        LHLD    HALFBIT ⟨16⟩
```

Loop for one-half bit time before starting to sample data:

```
CI2:    DCR     L       ⟨D⟩
        JNZ     CI2     ⟨D⟩
        DCR     H       ⟨D⟩
        JNZ     CI2     ⟨D⟩
```

Wait until the middle of the next bit before sampling SID, then move the data bit into CY:

```
CI3:    LHLD    BITTIME ⟨16⟩
CI4:    DCR     L       ⟨D⟩
        JNZ     CI4     ⟨D⟩
        DCR     H       ⟨D⟩
        JNZ     CI4     ⟨D⟩
        RIM             ⟨4⟩
        RAL             ⟨4⟩
```

Decrement the bit counter. If this is the ninth cycle, the 8 data bits are in register C, so quit (the first stop bit will already have been received, and be in CY):

```
        DCR     B       ⟨4⟩
        JZ      CI5     ⟨7⟩
```

Otherwise, continue. Rotate the data bit right into register C, and repeat the cycle:

```
        MOV     A,C     ⟨4⟩
        RAR             ⟨4⟩
        MOV     C,A     ⟨4⟩
        NOP             ⟨4⟩
        JMP     CI3     ⟨10⟩
```

(A NOP is needed to make the COUT and CIN loops exactly equal in number of machine cycles, so that each can use the same delay parameter.) Restore status and return.

```
CI5:    POP     H
        EI
        RET
```

TIMING ANALYSIS

COUT and CIN now need to be provided with parameters for BITTIME and HALFBIT. It can be seen from the above code that each routine uses 61 + D machine cycles per input or output bit, where D is the number of cycles spent in either four line delay segment. If ⟨H⟩ and ⟨L⟩ are the contents of the H and L registers going into this section of code, then:

$$D = 22 + ((L) - 1) \times 14 + ((H) - 1) \times [(255 \times 14) + 25] \quad (1)$$

If $\langle H\rangle' \equiv \langle H\rangle - 1$, $\langle L\rangle' \equiv \langle L\rangle - 1$, and

$$\langle HL\rangle' \equiv 256\,\langle H\rangle' + \langle L\rangle' \quad (2)$$

then

$$D = 22 + 14\,\langle L\rangle' + 3595\,\langle H\rangle' \quad (3)$$

This can be approximated by:

$$D = 22 + 14\,\langle HL\rangle' \quad (4)$$

This approximation is exact for $\langle H\rangle' = 0$; otherwise, it is accurate to within 0.3%. Thus each loop of COUT or CIN uses a total of:

$$C = 61 + D = 83 + 14\,\langle HL\rangle' \text{ machine cycles} \quad (5)$$

Each machine cycle uses two crystal cycles in the 8085, so the resulting data rate is:

$$B = \frac{\text{cycle frequency}}{C}$$

$$= \frac{(\text{crystal frequency}) \div 2}{83 + 14\,\langle HL\rangle'} \quad (6)$$

For a typical calculation, see Example 4.

EXAMPLE 4

To produce 2400 baud with the standard 6.144 MHz crystal:

$$2400 = \frac{(6.144 \times 10^6) \div 2}{83 + 14\langle HL\rangle'}$$

$$14\langle HL\rangle' = \left(\frac{6.144 \times 10^6 \div 2}{2400}\right) - 83$$

$$\langle HL\rangle' = \left[\left(\frac{6.144 \times 10^6 \div 2}{2400}\right) - 83\right] \div 14 = 85.5 \cong 86$$

$$\langle HL\rangle' = 86_{10} = 0056H$$

$$\langle HL\rangle = 0157H = BITTIME$$

To determine the true data rate this parameter will produce, substitute into equation (6):

$$\text{Date Rate} = \frac{6.144 \times 10^6 \div 2}{83 + 14(86)}$$

$$= 2387 \text{ baud, which is } 0.54\% \text{ slow.}$$

For 9600 baud, the same calculations will yield $\langle HL\rangle' = 17$, which is actually 0.3% slow; a sizzling 19200 baud or 38400 baud could each be generated to within 5% if $\langle HL\rangle' = 6$ or 0! Table 1 presents the parameters for several standard baud rates.

Notice that the resolution of the delay algorithm – the difference between bit times resulting from parameters which differ by one – is 14 machine cycles. As a result, the true bit delay produced can always manage to be within ±2.3 μsec of the delay desired. This guarantees that at rates up to 9600 baud, where each bit time is at least 104 μsec wide, some value of BITTIME can be found which will be accurate to within 2.2%.

BAUD RATE IDENTIFICATION ROUTINE

The function of BRID is to compute the appropriate parameters BITTIME and HALFBIT. It accomplishes this by observing the data pattern received when the space bar is pressed on the console device. Since a space character has the ASCII code 20H = 00100000B, the pattern represented back in Figure 4 is transmitted. Notice that the initial zero level is 6 bits wide. Suppose it could be determined that this corresponds to M machine cycles. Then one bit would correspond to (M÷6) machine cycles. The reason for dividing down a space several bits long is so that any distortion caused by the signal rise and fall times, or any lack of precision in detecting the two transitions, will be reduced by a factor of six. Since the bit period of COUT and CIN is $83 + 14\langle HL\rangle'$, BRID must generate a value $\langle HL\rangle'$ such that:

$$M \div 6 = 83 + 14\langle HL\rangle' \quad (7)$$

$$\langle HL\rangle' = \frac{(M \div 6) - 83}{14} \quad (8)$$

$$\langle HL\rangle' = \frac{M}{84} - 6 \text{ (approximately)} \quad (9)$$

This value can be determined by setting register pair HL to –6, then incrementing it once every 84 machine cycles during the period that the incom-

Table 1

DELAY PARAMETERS FOR STANDARD BAND RATES USING 6.144 MHz CRYSTAL

TARGET BAUD RATE	$\langle HL\rangle'_{10}$ (See Text)	$\langle HL\rangle'_{16}$ (See Text)	$\langle HL\rangle$ or BITTIME (See Text)	HALFBIT	ACTUAL BAUD RATE PRODUCED	% ERROR
110	1989	07C5	08C6	04E3	109.99	-0.006
150	1457	05B1	06B2	03D9	149.99	-0.005
300	726	02D6	03D7	026C	299.80	-0.068
600	360	0168	0269	01A5	599.65	-0.059
1200	177	00B1	01B2	0159	1199.5	-0.039
2400	86	0056	0157	012C	2386.9	-0.547
4800	40	0028	0129	0115	4777.6	-0.469
9600	17	0011	0112	0109	9570.1	-0.312
19200	6	0006	0107	0104	18395.2	-4.37

ing signal is zero. BITTIME is then obtained by individually incrementing registers H and L. To obtain HALFBIT, divide the value of ⟨HL⟩ determined above by two before incrementing each register.

In order to implement this algorithm, set HL to –6, verify that the incoming signal is a logic one, then wait for the start bit transition.

```
BRID:   MVI     A,00H
        SIM
        LXI     H,-6H
BRI1:   RIM
        ORA     A
        JP      BRI1
BRI2:   RIM
        ORA     A
        JM      BRI2
```

Increment register pair HL, then delay so that each cycle will require 84 machine cycles:

```
BRI3:   INX     H           ⟨6⟩
        MVI     E,04H       ⟨7⟩
BRI4:   DCR     E           (53)
        JNZ     BRI4        (''')
```

Check if SID is still low. If so, repeat:

```
        RIM                 ⟨4⟩
        ORA     A           ⟨4⟩
        JP      BRI3        ⟨10⟩
```

Otherwise continue. Store HL temporarily for the HALFBIT calculation. Obtain and store BITTIME:

```
        PUSH    H
        INR     H
        INR     L
        SHLD    BITTIME
```

Restore HL, calculate HALFBIT, and return:

```
        POP     H
        ORA     A
        MOV     A,H
        RAR
        MOV     H,A
        MOV     A,L
        RAR
        MOV     L,A
        INR     H
        INR     L
        SHLD    HALFBIT
        RET
```

The assembled listings for these subroutines, along with a simple test program, is presented in the Appendix.

CASSETTE RECORDER INTERFACE

There are many situations where data has to be transmitted through a non-ideal medium. To give three typical examples, a system with electrically isolated elements might require that signals be AC coupled, communications through an audio network (such as telephone or radio) are greatly bandwidth limited, and some applications (such as a distributed network in an industrial environment) must tolerate random electrical noise. Attempting to record data on a cheap cassette recorder (the one used for this note cost $17.00) will reveal all of these shortcomings, plus one: The tape speed fluctuates significantly and varies as the batteries run down, hence the data rate is inconsistent.

The recording scheme used here makes very few demands on the transmission medium. It makes no attempt to transmit DC voltage levels. Instead, data is transmitted by a series of variable length tone bursts. The dominant frequency of the tone used can be selected to be within the passband of the particular medium. Data is transmitted with each bit composed of a tone burst followed by a pause. The first third of a bit period is always a tone burst, the middle third is either a tone burst continuous with the first or a pause corresponding to, respectively, a one or zero, and the final third is always a pause, as shown in Figure 7. Thus, data is distinguished by the burst/pause ratio.

Hardware Design

These tone bursts are obtained from the 8085 SOD line, using analog signal conditioning to eliminate the DC component of the waveform. (This low frequency component is due to the single-ended nature of the SOD line: it's deviations from ground are all positive, which unbalances the capacitive input stage of the recorder.) A suggested interface circuit is shown in Figure 8, using one LM324 quad op amp and a few standard value discrete components which should be available in even a digital design laboratory. On playback, analog circuitry is again used to detect the presence of a tone burst. In Figure 8, A2 buffers the incoming signal, and A3 inverts it. The peaks of these two signals are transmitted through D1 or D2 and are filtered by an RC network. Comparator A4 then squares up the output and produces the logic signal read

by the SID pin. Since the op amps are powered by the single 5-volt supply, a 2.0-volt reference level is obtained from a resistive voltage divider. The waveforms present at several points in the circuit are shown in Figure 9.

Software

The algorithm for reading a data bit off the tape is simple and straightforward: If the tone burst is longer than the pause, the bit is a one. Otherwise, it is a zero. Since only the time ratio is considered, any variation in tape speed will not affect the data determination.

VOLUME CONTROL

A question that arises with any audio cassette interface is how to set the volume control. (Recording level is usually determined internally.) When the playback level is correct, the logic signal output from A4 will have either a one-third or two-thirds duty cycle. This can be readily observed with an oscilloscope. In the field, an old-fashioned mechanical-type voltmeter could be connected to the A4 output, and the volume adjusted until the meter needle hovered somewhere between 1/3 and 2/3 the high level output voltage. With random data, the reading would be about 2 volts. There will be a fairly wide range of acceptable volume settings. (Since the quivering meter needle is being used here for inertial signal averaging, a digital voltmeter would not be very helpful in this application.)



Figure 7. Tape Interface Data Recording Scheme



Figure 8. One Chip Magnetic Tape Interface Schematic



Figure 9. Analog Signal Waveforms

After the CRT software analysis, the tape routines are almost trivial. TAPEO is a subroutine for outputting the contents of register C to a cassette recorder. TAPEIN reads 8 bits into register C.

OUTPUT ROUTINE

TAPEO calls a subroutine named BURST three times for each bit. If A_6 (the SOD enable bit) is set when BURST is called, a square-wave tone burst will be transmitted. If A_6 is not set, BURST simply delays for exactly the same amount of time before returning. The three calls are used to, respectively, output the initial burst, output the data burst/space, and create the space at the end of each bit. Nine bits will be output: the eight data bits (LSB first) followed by a zero bit. The start of the initial burst of the trailing zero is needed to mark the end of the final space of the preceding data bit.

Start each bit by outputting a tone burst:

```
TAPEO:  MVI     B,9
TO1:    MVI     A,0C0H
        CALL    BURST
```

Rotate register C through CY:

```
        MOV     A,C
        RAR
        MOV     C,A
```

Move CY to the SOD enable bit position, A_6. Simultaneously set A_7 to one, and clear all other bits. Output a tone burst or space, depending on the previous contents of CY:

```
        MVI     A,01H
        RAR
        RAR
        CALL    BURST
```

Clear the accumulator, and output a space:

```
        XRA     A
        CALL    BURST
```

Keep cycling until the full 9-bit sequence is finished:

```
        DCR     B
        JNZ     TO1
        RET
```

The BURST subroutine executes the SIM instruction CYCNO times, at intervals of 29 + 14 ⟨HALFCYC⟩ machine cycles. In between each SIM, bit A_7 is complemented. CYCNO should be an even number. If A_6 is set upon calling BURST a square-wave will be created. Otherwise, the same code sequence is followed but SOD does not change – thus a space results.

```
BURST:  MVI     D,CYCNO         ⟨7⟩
BU1:    SIM                     ⟨4⟩
        MVI     E,HALFCYC       ⟨7⟩
BU2:    DCR     E               ⟨4⟩
        JNZ     BU2           ⟨7/10⟩
        XRI     80H             ⟨7⟩
        DCR     D               ⟨4⟩
        JNZ     BU1           ⟨7/10⟩
        RET                    ⟨10⟩
```

INPUT ROUTINE

TAPEIN uses a subroutine called BITIN to move the data at the SID pin into the CY. The maximum rate at which SID is read is limited by a delay loop in BITIN.

Initialize the bit counter and the register D, which will keep track of the tone burst time. If a tone

burst is being received when TAPEIN is called, wait until the burst is over:

```
TAPEIN: MVI     B,8
        MVI     D,00H
TI1:    CALL    BITIN
        JC      TI1
        CALL    BITIN
        JC      TI1
```

(Throughout this subroutine, a level transition is recognized only after it has been read once initially and then verified on the next reading. This provides some degree of software noise immunity.) Now await the start of the next burst:

```
TI2:    CALL    BITIN
        JNC     TI2
        CALL    BITIN
        JNC     TI2
```

The next burst has now arrived. Keep reading the SID pin, decrementing register D (thus making it more negative), each cycle until the pause is detected:

```
TI3:    DCR     D
        CALL    BITIN
        JC      TI3
        CALL    BITIN
        JC      TI3
```

Now continue reading the SID pin, incrementing the D register (back towards zero), each cycle until the next burst is received:

```
TI4:    INR     D
        CALL    BITIN
        JNC     TI4
        CALL    BITIN
        JNC     TI4
```

Now, if the burst lasted longer than the space, D was not incremented all the way back to zero; it is still negative. If the space was longer, D was incremented up through zero; it is now positive. In other words, the sign bit of D will now correspond to the data bit that would lead to each of these results. Move the sign bit into the CY, then rotate it into register C:

```
        MOV     A,D
        RAL
        MOV     A,C
        RAR
        MOV     C,A
        MVI     D,00H
```

Continue until the last bit has been received:

```
        DCR     B
        JNZ     TI3
        RET
```

(Notice that the first half of this subroutine is incorporated in the second half. In fact, the assembled listing included in the Appendix makes use of this fact to eliminate 24 bytes of duplicated code.)

BITIN waits a short time in order to regulate the sampling rate, then reads SID and moves the data bit into the CY:

```
BITIN:  MVI     E,CKRATE        <7>
BI1:    DCR     E               <4>
        JNZ     BI1             <7/10>
        RIM                     <4>
        RAL                     <4>
        RET                     <10>
```

The tone burst frequency and duration, and the TAPEIN sampling rate are determined by HALFCYC, CYCNO, and CKRATE. Tables 2 and 3 give typical values.

Table 2

EXAMPLE COMBINATIONS OF HALFCYC AND CYCNO. ALL VALUES IN DECIMAL

APPROXIMATE TONE FREQUENCY	CORRESPONDING HALFCYC VALUE	RESULTING DATA RATE			
		8 4	20 10	100 50	CYCNO CYC/BURST
500 Hz	217	42	17	3.3	bps
1 kHz	108	83	33	6.6	bps
2 kHz	53	166	66	13	bps
5 kHz	20	414	166	33	bps
10 kHz	9	826	330	66	bps

Table 3

MAXIMUM SAMPLING RATES FOR VARIOUS VALUES OF CKRATE

CKRATE VALUE	SAMPLING RATE (INCLUDING CALL & RET)
1	17.6 μsec
20	104 μsec
80	378 μsec
250	1.14 msec

The Appendix also includes a simple block record routine utilizing TAPEO. Before calling BLKRCD, HL must be set to the start of the desired block, and the recorder turned on manually. Successive bytes will be recorded until the end of that page, i.e., until L is incremented to zero. The playback routine requires presetting HL to the target address and turning on the recorder before PLAYBK is called. These routines incorporate a long tone burst before each data block to allow a recorder with Automatic Gain Control to stabilize before the data starts.

ADDITIONAL COMMENTS

The two design examples given so far were built up using an SDK-85 System Design Kit. Both hardware interfaces were wire-wrapped on the ample breadboarding area provided on the board. The connections between SID and SOD and the on-board TTY interface were broken, so as not to affect the 8085 I/O electrical characteristics.

The CRT interface was tested with a Beehive Mini-Bee II Terminal in the full duplex mode at each of its 14 possible transmission rates, from 110 to 9600 baud. It was also checked out at 19200 baud using a Beehive B-100 terminal. In addition, the software was exercised using an SBC 80/20 system as a variable baud rate character generator and receiver.

An additional advantage to having software selectable communications rates is that it would be possible to communicate with several system periperals, each at its own preferred rate, without having to duplicate hardware. For example, the addition of a single 7408 AND gate and an output port (such as on the 8155) would make it possible to use the same two RS-232 circuits to interface with up to seven I/O devices (see Figure 10). Three of the MC1488 drivers have Enable inputs which can be controlled by the output port. One AND gate can be used to buffer the SOD line and drive the MC1488 Data inputs. The rest of the 7408 can be configured as a four input AND gate. This would act as an inverted logic OR gate to reduce the four MC1489 receiver outputs to a single line, which could be read by the SID. This assumes that only one input device (CRT, PTR) at a time will be used (which is usually the case in a non-time shared, interactive application), and that the unused devices are transmitting a logic one level (which should also be the case).



Figure 10. Interfacing 8085 to Multiple Peripherals

The software needed to support additional peripherals would be simple and straightforward. A routine intended to dump a section of memory to a paper tape punch, for example, would first have to store BITTIME and HALFBIT somewhere (perhaps on stack), load the variables with new parameters corresponding to the paper tape punch rate, and then write a bit pattern to the output port which would disable the console driver and enable the punch (and perhaps a typewriter). After the dump was over, the original time parameters and driver status would be restored.

As explained before, the BRID routine computed rate parameters based on the fact that an ASCII "space" character resulted in a zero level 6 bits long. Conceivably, some obscure peripherals might produce a transient between successive zero bits. (This might be the case, for example, if the signal was produced by mechanical rather than electronic means.) If so, the BRID algorithm used here probably would not work reliably. Once the two time parameters were identified, though, COUT and CIN could still be used. An alternate algorithm for baud rate identification would require a table in ROM (note the fifth and final R/S-I/O-M/D permutation). This table would contain a list of delay parameters corresponding to the standard transmis-

sion rates, as computed for the selected crystal frequency. Initialization would require the operator to hit a specific key several times (usually the "U" key, which generates a pattern of alternating ones and zeros). The identification routine would attempt to "read" this pattern at each baud rate, in turn, until finding the rate at which the read was successful.

The cassette recorder used to develop the tape interface was a Lloyd's push-button model which cost $17 in 1972. Empirical testing has indicated that for this application, the quality of the cassette recorder is less critical than the quality of the tape itself. In other words, some 33¢ cassettes were not very reliable, even when used with more expensive recorders.

When using a cassette at the beginning of a side, allow the tape to run for about 10 seconds until the leader has passed before starting to write data. Otherwise, data will be lost to the leader.

Depending on the recorder quality, the tone burst frequency and duration can be optimized for higher data rates by modifying HALFCYC and CYCNO. If so, CKRATE should also be reduced, so that between about 10 and 80 data samplings are made during a single (one-third width) tone burst. At greatly increased frequencies, some of the components in the analog interface might also be modified.

The two simple routines for recording and playing back blocks of data were intended to illustrate one way of using TAPEIN and TAPEO, and therefore do not contain any provisions for error detection or correction. Depending on the nature of a particular application, these routines could be augmented with parity bit or checksum comparison, or an error correcting code technique.

Funny things happen when recording and playing back a page of RAM which includes the subroutine stack. Eventually, PLAYBK will start writing over the data at the top of the stack, destroying the subroutine traceback sequence. The next RET instruction will then cause a jump to a place where you'd rather not be.

The printout reproduced in the Appendix includes the assembled listings for the CRT and magnetic tape interfaces discussed in this application note. The object code produced was programmed into an 8755 EPROM, which was installed in the expansion PROM socket of the SDK-85 board. Some very minor differences exist between this listing and the code segments presented earlier, which were written for maximum clarity.

APPENDIX

```
ISIS-II 8080/8085 ASSEMBLER, V1.0        MODULE                    PAGE    1

 LOC  OBJ          SEQ          SOURCE STATEMENT

                      0 $   MOD85 TITLE('8085 SERIAL I/O NOTE APPENDIX')
```

```
LOC  OBJ        SEQ        SOURCE STATEMENT

                    1
                    2 ;       THE FOLLOWING PROGRAMS AND SUBROUTINES ARE DESCRIBED IN DETAIL
                    3 ;       IN INTEL CORPERATION'S APPLICATION NOTE AP-29, "USING THE 8085
                    4 ;       SERIAL I/O LINES".  THE FIRST SECTION IS A GENERAL PURPOSE CRT
                    5 ;       INTERFACE WITH AUTOMATIC BAUD RATE IDENTIFICATION; THE SECOND
                    6 ;       SECTION IS A MAGNETIC TAPE INTERFACE FOR STORING DATA ON CASSETTE
                    7 ;       TAPES.  THE CODE PRESENTED HERE IS ORIGINED AT LOCATION 800H,
                    8 ;       AND MIGHT BE PART OF AN EXPANSION PROM IN AN INTEL SDK-85
                    9 ;       SYSTEM DESIGN KIT.
                   10 ;
                   11
                   12
20C8               13 BITTIME EQU     20C8H   ;ADDRESS OF STORAGE FOR COMPUTED BIT DELAY
20CA               14 HALFBIT EQU     20CAH   ;ADDRESS OF STORAGE  FOR HALF BIT DELAY
0008               15 BITSO   EQU     11      ;DATA BITS PUT OUT (INCLUDING TWO STOP BITS)
0009               16 BITSI   EQU     9       ;DATA BITS TO BE RECIEVED (INCLUDING ONE STOP BIT)
                   17
0800               18         ORG     800H    ;STARTING ADDRESS OF SDK-85 EXPANSION PROM
                   19
                   20 ;CRTTST CRT INTERFACE TEST.  WHEN CALLED, AWAITS THE SPACE BAR BEING PRESSED ON
                   21 ;       THE SYSTEM CONSOLE, AND THEN RESPONDS WITH A DATA RATE VERIFICATION
                   22 ;       MESSAGE.  THERE AFTER, CHARACTERS TYPED ON THE KEYBOARD ARE ECHOED
                   23 ;       ON THE DISPLAY TUBE.  WHEN A BREAK KEY IS TYPED, THE ROUTINE IS
                   24 ;       RE-STARTED, ALLOWING A DIFFERENT BAUD RATE TO BE SELECTED ON THE CRT.
0800 31C020        25 CRTTST: LXI     SP,20C0H
0803 3EC0          26 CRT1:   MVI     A,0C0H  ;SOD MUST BE HIGH BETWEEN CHARACTERS
0805 30            27         SIM
0806 CD1A08        28         CALL    BRID    ;IDENTIFY DATA RATE USED BY TERMINAL
0809 CD4708        29         CALL    SIGNON  ;OUTPUT SIGNON MESSAGE AT RATE DETECTED
080C CD8A08        30 ECHO:   CALL    CIN     ;READ NEXT KEYSTROKE INTO REGISTER C
080F 79            31         MOV     A,C
0810 B7            32         ORA     A       ;CHECK IF CHARACTER WAS A <BREAK> (ASCII 00H)
0811 CA0308        33         JZ      CRT1    ;IF SO, RE-IDENTIFY DATA RATE
                   34                         ;THIS ALLOWS ANOTHER RATE TO BE SELECTED ON CRT
0814 CD6908        35         CALL    COUT    ;OTHERWISE COPY REGISTER C TO THE SCREEN
0817 C30C08        36         JMP     ECHO    ;CONTINUE INDEFINITELY (UNTIL BREAK)
                   37
                   38 ;BRID   BAUD RATE IDENTIFICATION SUBROUTINE
                   39 ;       EXPECTS A <CR> (ASCII 20H) TO BE RECIEVED FROM THE CONSOLE.
                   40 ;       THE LENGTH OF THE INITIAL ZERO LEVEL (SIX BITS WIDE) IS MEASURED
                   41 ;       IN ORDER TO DETERMINE THE DATA RATE FOR FUTURE COMMUNICATIONS.
081A 20            42 BRID:   RIM             ;VERIFY THAT THE "ONE" LEVEL HAS BEEN ESTABLISHED
081B B7            43         ORA     A       ;\ AS THE CRT IS POWERING UP
081C F21A08        44         JP      BRID
081F 20            45 BRI1:   RIM             ;MONITOR SID LINE STATUS
0820 B7            46         ORA     A
0821 FA1F08        47         JM      BRI1    ;LOOP UNTIL START BIT IS RECIEVED
0824 21FAFF        48         LXI     H,-6    ;BIAS COUNTER USED IN DETERMINING ZERO DURATION
0827 1E04          49 BRI3:   MVI     E,04H
0829 1D            50 BRI4:   DCR     E       ;53 MACHINE CYCLE DELAY LOOP
082A C22908        51         JNZ     BRI4
082D 23            52         INX     H       ;INCREMENT COUNTER EVERY 84 CYCLES WHILE SID IS LOW
082E 20            53         RIM
```

```
LOC  OBJ        SEQ        SOURCE STATEMENT

082F B7          54        ORA     A
0830 F22708      55        JP      BRI3
                 56                        ;<HL> NOW CORRESPONDS TO INCOMING DATA RATE
0833 E5          57        PUSH    H       ;SAVE COUNT FOR HALFBIT TIME COMPUTATION
0834 24          58        INR     H       ;BITTIME IS DETERMINED BY INCREMENTING
0835 2C          59        INR     L       ;\ H AND L INDIVIDUALLY
0836 22C820      60        SHLD    BITTIME
0839 E1          61        POP     H       ;RESTORE COUNT FOR HALFBIT DETERMINATION
083A B7          62        ORA     A       ;CLEAR CARRY
083B 7C          63        MOV     A,H     ;ROTATE RIGHT EXTENDED <HL>
083C 1F          64        RAR             ;\ TO DIVIDE COUNT BY 2
083D 67          65        MOV     H,A
083E 7D          66        MOV     A,L
083F 1F          67        RAR
0840 6F          68        MOV     L,A
0841 24          69        INR     H       ;PUT H AND L IN PROPER FORMAT FOR DELAY
0842 2C          70        INR     L       ;\ SEGMENTS (INCREMENT EACH)
0843 22CA20      71        SHLD    HALFBIT ;SAVE AS HALF-BIT TIME DELAY PARAMETER
0846 C9          72        RET
                 73
                 74 ;SIGNON WRITES A SIGN-ON MESSAGE TO THE CRT AT WHAT SHOULD BE THE CORRECT RATE.
                 75 ;       IF THE MESSAGE IS UNINTELLIGIBLE. . . WELL, SO IT GOES.
0847 215508      76 SIGNON: LXI     H,STRNG ;LOAD START OF SIGN-ON MESSAGE
084A 4E          77 S1:     MOV     C,M     ;GET NEXT CHARACTER
084B AF          78         XRA     A       ;CLEAR ACCUMULATOR
084C B1          79         ORA     C       ;CHECK IF CHARACTER IS END OF STRING
084D C8          80         RZ              ;RETURN IF SIGN-ON COMPLETE
084E CD6908      81         CALL    COUT    ;ELSE OUTPUT CHARACTER TO CRT
0851 23          82         INX     H       ;INDEX POINTER
0852 C34A08      83         JMP     S1      ;ECHO NEXT CHARACTER
                 84
0855 0D          85 STRNG:  DB      0DH,0AH ;<CR><LF>
0856 0A
0857 42415544    86         DB      'BAUD RATE CHECK'
085B 20524154
085F 45204348
0863 45434B
0866 0D          87         DB      0DH,0AH ;<CR><LF>
0867 0A
0868 00          88         DB      00H     ;END-OF-STRING ESCAPE CODE
                 89
                 90 ;COUT   CONSOLE OUTPUT SUBROUTINE
                 91 ;       WRITES THE CONTENTS OF THE C REGISTER TO THE CRT DISPLAY SCREEN
0869 F3          92 COUT:   DI
086A C5          93         PUSH    B
086B E5          94         PUSH    H
086C 060B        95         MVI     B,BITSO ;SET NUMBER OF BITS TO BE TRANSMITTED
086E AF          96         XRA     A       ;CLEAR CARRY
086F 3E80        97 CO1:    MVI     A,80H   ;SET WHAT WILL BECOME SOD ENABLE BIT
0871 1F          98         RAR             ;MOVE CARRY INTO SOD DATA BIT OF ACC
0872 30          99         SIM             ;OUTPUT DATA BIT TO SOD
0873 2AC820     100         LHLD    BITTIME
0876 2D         101 CO2:    DCR     L       ;WAIT UNTIL APPROPRIATE TIME HAS PASSED
```

```
 LOC  OBJ        SEQ        SOURCE STATEMENT

 0877 C27608      102        JNZ    CO2
 087A 25          103        DCR    H
 087B C27608      104        JNZ    CO2
 087E 37          105        STC            ;SET WHAT WILL EVENTUALLY BECOME A STOP BIT
 087F 79          106        MOV    A,C     ;ROTATE CHARACTER RIGHT ONE BIT,
 0880 1F          107        RAR            ;\ MOVING NEXT DATA BIT INTO CARRY
 0881 4F          108        MOV    C,A
 0882 05          109        DCR    B       ;CHECK IF CHARACTER (AND STOP BIT(S)) DONE
 0883 C26F08      110        JNZ    CO1     ;IF NOT, OUTPUT CURRENT CARRY
 0886 E1          111        POP    H       ;RESTORE STATUS AND RETURN
 0887 C1          112        POP    B
 0888 FB          113        EI
 0889 C9          114        RET
                  115
                  116 ;CIN    CONSOL INPUT SUBROUTINE WAITS FOR A KEYSTROKE AND
                  117 ;       RETURNS WITH 8 BITS IN REG C.
 088A F3          118 CIN:   DI
 088B E5          119        PUSH   H
 088C 0609        120        MVI    B,BITSI ;DATA BITS TO BE READ (LAST RETURNED IN CY)
 088E 20          121 CI1:   RIM            ;WAIT FOR SYNC BIT TRANSITION
 088F B7          122        ORA    A
 0890 FA8E08      123        JM     CI1
 0893 2ACA20      124        LHLD   HALFBIT
 0896 2D          125 CI2:   DCR    L       ;WAIT UNTIL MIDDLE OF START BIT
 0897 C29608      126        JNZ    CI2
 089A 25          127        DCR    H
 089B C29608      128        JNZ    CI2
 089E 2AC820      129 CI3:   LHLD   BITTIME ;WAIT OUT BIT TIME
 08A1 2D          130 CI4:   DCR    L
 08A2 C2A108      131        JNZ    CI4
 08A5 25          132        DCR    H
 08A6 C2A108      133        JNZ    CI4
 08A9 20          134        RIM            ;CHECK SID LINE LEVEL
 08AA 17          135        RAL            ;DATA BIT IN CY
 08AB 05          136        DCR    B       ;DETERMINE IF THIS IS FIRST STOP BIT
 08AC CAB608      137        JZ     CI5     ;IF SO, JUMP OUT OF LOOP
 08AF 79          138        MOV    A,C     ;ELSE ROTATE INTO PARTIAL CHARACTER IN C
 08B0 1F          139        RAR            ;ACC HOLDS UPDATED CHARACTER
 08B1 4F          140        MOV    C,A
 08B2 00          141        NOP            ;EQUALIZES COUT AND CIN LOOP TIMES
 08B3 C39E08      142        JMP    CI3
 08B6 E1          143 CI5:   POP    H
 08B7 FB          144        EI
 08B8 C9          145        RET            ;CHARACTER COMPLETE
                  146
                  147 ;*****************************************************************************
                  148
                  149 ;       THE FOLLOWING CODE IS USED BY THE CASSETTE INTERFACE.
                  150 ;       SUBROUTINES TAPEO AND TAPEIN ARE USED RESPECTIVELY
                  151 ;       TO OUTPUT OR RECEIVE AN EIGHT BIT BYTE OF DATA.  REGISTER C
                  152 ;       HOLDS THE DATA IN EITHER CASE.  REGISTERS A,B,&C ARE ALL DESTROYED.
 0010             153 CYCNO  EQU    16      ;TWICE THE NUMBER OF CYCLES PER TONE BURST
 001E             154 HALFCYC EQU   30      ;DETERMINES TONE FREQUENCY
```

```
LOC  OBJ        SEQ        SOURCE STATEMENT

0016             155 CKRATE  EQU     22      ;SETS SAMPLE RATE
00FA             156 LEADER  EQU     250     ;NUMBER OF SUCCESIVE TONE BURSTS COMPRISING LEADER
00FA             157 LDRCHK  EQU     250     ;USED IN PLAYBK TO VERIFY PRESENCE OF LEADER
                 158
                 159 ;BLKRCD         OUTPUTS A VERY LONG TONE BURST (<LEADER> TIMES
                 160 ;               THE NORMAL BURST DURATION) TO ALLOW RECORDER ELECTRONICS
                 161 ;               AND AGC TO STABILIZE.  THEN OUTPUTS THE REMAINDER OF THE
                 162 ;               256 BYTE PAGE POINTED TO BY <H>, STARTING AT BYTE <L>.
08B9 0EFA        163 BLKRCD: MVI     C,LEADER;SET UP LEADER BURST LENGTH
08BB 3EC0        164         MVI     A,0C0H  ;SET ACCUMULATOR TO RESULT IN TONE BURST
08BD CDF008      165 BR1:    CALL    BURST   ;OUTPUT TONE
08C0 0D          166         DCR     C
08C1 C2BD08      167         JNZ     BR1     ;SUSTAIN LEADER TONE
08C4 AF          168         XRA     A       ;CLEAR ACCUMULATOR & OUTPUT SPACE, SO THAT
08C5 CDF008      169         CALL    BURST   ;\ START OF FIRST DATA BYTE CAN BE DETECTED
08C8 4E          170 BR2:    MOV     C,M     ;GET DATA BYTE TO BE RECORDED
08C9 CDD108      171         CALL    TAPEO   ;OUTPUT REGISTER C TO RECORDER
08CC 2C          172         INR     L       ;POINT TO NEXT BYTE
08CD C2C808      173         JNZ     BR2
08D0 C9          174         RET             ;AFTER BLOCK IS COMPLETE
                 175
                 176
                 177 ;TAPEO          OUTPUTS THE BYTE IN REGISTER C TO THE RECORDER.
                 178 ;               REGISTERS A,B,C,D,&E ARE ALL USED.
08D1 F3          179 TAPEO:  DI
08D2 D5          180         PUSH    D       ;D&E USED AS COUNTERS BY SUBROUTINE BURST
08D3 0609        181         MVI     B,9     ;WILL RESULT IN 8 DATA BITS AND ONE STOP BIT
08D5 AF          182 TO1:    XRA     A       ;CLEAR ACCUMULATOR
08D6 3EC0        183         MVI     A,0C0H  ;SET ACCUMULATOR TO CAUSE A TONE BURST
08D8 CDF008      184         CALL    BURST
08DB 79          185         MOV     A,C     ;MOVE NEXT DATA BIT INTO THE CARRY
08DC 1F          186         RAR
08DD 4F          187         MOV     C,A     ;CARRY WILL BECOME SOD ENABLE IN BURST ROUTINE
08DE 3E01        188         MVI     A,01H   ;SET BIT TO BE REPEATEDLY COMPLEMENTED IN BURST
08E0 1F          189         RAR
08E1 1F          190         RAR
08E2 CDF008      191         CALL    BURST   ;OUTPUT EITHER A TONE OR A PAUSE
08E5 AF          192         XRA     A       ;CLEAR ACCUMULATOR
08E6 CDF008      193         CALL    BURST   ;OUTPUT PAUSE
08E9 05          194         DCR     B
08EA C2D508      195         JNZ     TO1     ;REPEAT UNTIL BYTE FINISHED
08ED D1          196         POP     D       ;RESTORE STATUS AND RETURN
08EE FB          197         EI
08EF C9          198         RET
                 199
08F0 1610        200 BURST:  MVI     D,CYCNO ;SET NUMBER OF CYCLES
08F2 30          201 BU1:    SIM             ;COMPLEMENT SOD LINE IF SOD ENABLE BIT SET
08F3 1E1E        202         MVI     E,HALFCYC
08F5 1D          203 BU2:    DCR     E       ;REGULATE TONE FREQUENCY
08F6 C2F508      204         JNZ     BU2
08F9 EE80        205         XRI     80H     ;COMPLEMENT SOD DATA BIT IN ACCUMULATOR
08FB 15          206         DCR     D
08FC C2F208      207         JNZ     BU1     ;CONTINUE UNTIL BURST (OR EQUIVILENT PAUSE) FINISHED
```

```
LOC  OBJ        SEQ        SOURCE STATEMENT

08FF C9          208        RET
                 209
                 210 ;PLAYBK        WAITS FOR THE LONG LEADER BURST TO ARRIVE, THEN CONTINUES
                 211 ;              READING BYTES FROM THE RECORDER AND STORING THEM
                 212 ;              IN MEMORY STARTING AT LOCATION <HL>.
                 213 ;       CONTINUES UNTIL THE END OF THE CURRENT PAGE (<L>=0FFH) IS REACHED.
0900 0EFA        214 PLAYBK: MVI     C,LDRCHK        ;<LDRCHK> SUCCESSIVE HIGHS MUST BE READ
0902 CD3D09      215 PB1:    CALL    BITIN           ;\ TO VERIFY THAT THE LEADER IS PRESENT
0905 D20009      216         JNC     PLAYBK          ; \ AND ELECTRONICS HAS STABILIZED
0908 0D          217         DCR     C
0909 C20209      218         JNZ     PB1
090C CD1509      219 PB2:    CALL    TAPEIN  ;GET DATA BYTE FROM RECORDER
090F 71          220         MOV     M,C     ;STORE IN MEMORY
0910 2C          221         INR     L       ;INCREMENT POINTER
0911 C20C09      222         JNZ     PB2     ;REPEAT FOR REST OF CURRENT PAGE
0914 C9          223         RET
                 224
                 225 ;TAPEIN CASSETTE TAPE INPUT SUBROUTINE.  READS ONE BYTE OF DATA
                 226 ;       FROM THE RECORDER INTERFACE AND RETURNS WITH THE BYTE IN REGISTER C.
0915 0609        227 TAPEIN: MVI     B,9     ;READ EIGHT DATA BITS
0917 1600        228 TI1:    MVI     D,00H   ;CLEAR UP/DOWN COUNTER
0919 15          229 TI2:    DCR     D       ;DECREMENT COUNTER EACH TIME ONE LEVEL IS READ
091A CD3D09      230         CALL    BITIN
091D DA1909      231         JC      TI2     ;REPEAT IF STILL AT ONE LEVEL
0920 CD3D09      232         CALL    BITIN
0923 DA1909      233         JC      TI2
0926 14          234 TI3:    INR     D       ;INCREMENT COUNTER EACH TIME ZERO IS READ
0927 CD3D09      235         CALL    BITIN
092A D22609      236         JNC     TI3     ;REPEAT EACH TIME ZERO IS READ
092D CD3D09      237         CALL    BITIN
0930 D22609      238         JNC     TI3
0933 7A          239         MOV     A,D
0934 17          240         RAL             ;MOVE COUNTER MOST SIGNIFICANT BIT INTO CARRY
0935 79          241         MOV     A,C
0936 1F          242         RAR             ;MOVE DATA BIT RECIEVED (CY) INTO BYTE REGISTER
0937 4F          243         MOV     C,A
0938 05          244         DCR     B
0939 C21709      245         JNZ     TI1     ;REPEAT UNTIL FULL BYTE ASSEMBLED
093C C9          246         RET
                 247
093D 1E16        248 BITIN:  MVI     E,CKRATE
093F 1D          249 BI1:    DCR     E
0940 C23F09      250         JNZ     BI1     ;LIMIT INPUT SAMPLING RATE
0943 20          251         RIM             ;SAMPLE SID LINE
0944 17          252         RAL             ;MOVE DATA INTO CY BIT
0945 C9          253         RET
                 254
                 255         END


PUBLIC SYMBOLS
```

EXTERNAL SYMBOLS

USER SYMBOLS

BI1	A 093F	BITIN	A 093D	BITSI	A 0009	BITSO	A 000B	BITTIM	A 20C8	BLKRCD	A 08B9	BR1	A 08BD
BR2	A 08C8	BRI1	A 081F	BRI3	A 0827	BRI4	A 0829	BRID	A 081A	BU1	A 08F2	BU2	A 08F5
BURST	A 08F0	CI1	A 088E	CI2	A 0896	CI3	A 089E	CI4	A 08A1	CI5	A 08B6	CIN	A 088A
CKRATE	A 0016	CO1	A 086F	CO2	A 0876	COUT	A 0869	CRT1	A 0803	CRTTST	A 0800	CYCNO	A 0010
ECHO	A 080C	HALFBI	A 20CA	HALFCY	A 001E	LDRCHK	A 00FA	LEADER	A 00FA	PB1	A 0902	PB2	A 090C
PLAYBK	A 0900	S1	A 084A	SIGNON	A 0847	STRNG	A 0855	TAPEIN	A 0915	TAPEO	A 08D1	TI1	A 0917
TI2	A 0919	TI3	A 092E	TO1	A 0805								

ASSEMBLY COMPLETE, NO ERROR(S)

```
ISIS-II ASSEMBLER SYMBOL CROSS REFERENCE V1.0                    PAGE   1

BI1     249#   250
BITIN   215    230    232    235    237    248#
BITSI    16#   120
BITSO    15#    95
BITTIM   13#    60    100    129
BLKRCD  163#
BR1     165#   167
BR2     170#   173
BRI1     45#    47
BRI3     49#    55
BRI4     50#    51
BRID     28     42#    44
BU1     201#   207
BU2     203#   204
BURST   165    169    184    191    193    200#
CI1     121#   123
CI2     125#   126    128
CI3     129#   142
CI4     130#   131    133
CI5     137    143#
CIN      30    118#
CKRATE  155#   248
CO1      97#   110
CO2     101#   102    104
COUT     35     81     92#
CRT1     26#    33
CRTTST   25#
CYCNO   153#   200
ECHO     30#    36
HALFBI   14#    71    124
HALFCY  154#   202
LORCHK  157#   214
LEADER  156#   163
PB1     215#   218
PB2     219#   222
PLAYBK  214#   216
S1       77#    83
SIGNON   29     76#
STRNG    76     85#
TAPEIN  219    227#
TAPEO   171    179#
TI1     228#   245
TI2     229#   231    233
TI3     234#   236    238
TO1     182#   195

CROSS REFERENCE COMPLETE
```

Related Intel Publications

"8085 Microcomputer Systems User's Manual"

"8080/8085 Assembly Language Programming Manual"

INTEL CORPORATION, 3065 Bowers Avenue, Santa Clara, CA 95051 (408) 987-8080

Printed in U.S.A./T97/0578/20K BL